

ECE471: Embedded Systems – Homework 11
Power/Performance

Due: Friday, 7 December 2018, 10:00am EST

Power and Energy

Table 1: OpenBLAS HPL N=10000 (Matrix Multiply)

Machine	Processor	Cores	Frequency	Idle Power	Load Power	Time	Total Energy
Raspberry Pi 2	Cortex-A7	4	900MHz	1.8W	3.4W	454s	1543J
Dragonboard	Cortex-A53	4	1.2GHz	2.4W	4.7W	241s	1133J
Raspberry Pi 3	Cortex-A53	4	1.2GHz	1.8W	4.3W	178s	765J
Jetson-TX1	Cortex-A57	4	1.9GHz	2.1W	13.4W	47s	629J
Macbook Air	Broadwell	2	1.6GHz	10.0W	29.1W	14s	407J

1. Table 1 shows the energy use of various machines when doing a large Matrix-Matrix multiply.
 - (a) Which machine has the lowest under-load power draw?
 - (b) Which machine consumes the least amount of energy?
 - (c) Which machine computes the result fastest?
2. Consider a use case with an embedded board taking a picture once every 60 seconds and then performing a matrix-multiply similar to the one in the benchmark (perhaps for image-recognition purposes). Could all of the boards listed meet this deadline?
3. Assume a workload where a device takes a picture once a minute then does a large matrix multiply (as seen in Table 1). The device is idle when not multiplying, but under full load when it is.
 - (a) Over an hour, what is the total energy usage of the Jetson TX-1?
 - (b) Over an hour, what is the total energy usage of the Macbook Air?
4. Given your answer in the previous question, which device would you choose if you were running this project off of a battery?

Submitting the Assignment

Please put your answers to questions 1 - 4 in some sort of document (text, pdf, doc) and ***e-mail*** it to me by the deadline.